EV

x5 7000

CTEK

BATTERY CH

# FULLY AUTOMATIC, UNIVERSAL CHARGER AND MAINTAINER

The XS 7000 is the perfect universal charger you can just connect and forget. With no mode buttons to press, you simply plug it into the mains and connect the battery cables to start charging.

## AUTOMATIC DIAGNOSIS

The XS 7000 is a fully automatic 7 step charger that delivers 7A and charges 12V batteries from 14-150Ah, and is suitable for maintenance charging up to 225Ah. It features automatic battery diagnosis to establish whether your battery can receive and retain a charge, and you can follow the whole charging process on the clear, easy to read LED display.

### PRACTICAL AND SIMPLE TO USE

The XS 7000 charger is a practical and simple to use charger with an easy to understand display, It is nonsparking, reverse polarity protected and short-circuit proof, and comes with a 5 year warranty.

- Fully automatic 7 step charging
- Splash and dust proof (IP65)
- 2-year warranty..
- Patented maintenance charging up to 225Ah for longer life batteries
- Automatic battery diagnosis
- Charges 12V batteries from 14-150Ah
- Patented desulphation function
- Easy to read LED display
- Comes with Connect Eyelet connectors and Connect Clamp connectors

СТЕК

- Safe spark free operation
- Reverse polarity protected
- Short circuit proof

# XS 7000

RESET



# TECHNICAL DATA

INPUT	170-260 VAC, 50-60 Hz
OUTPUT	14.4 V, 7.0 A
CHARGER TYPE	Multistage fully automatic charger
BATTERY TYPES	12 V: WET, MF, AGM, GEL
BATTERY CAPACITY	14-225 Ah
BACK CURRENT DRAIN*	Corresponding to less than 1 Ah/month
AMBIENT OPERATING TEMPERATURE	-20 °C to +50 °C
BATTERY CHEMISTRY	Lead acid
DEGREE OF PROTECTION	IP65
WARRANTY	2 years

RECOND

BATTERY CH

#### **GUARANTEED QUALITY WITH CTEK**

CTEK customer support is available to answer any questions related to charging and CTEK chargers. Safety, simplicity and flexibility characterizes all products and solutions developed and sold by CTEK. CTEK supply chargers to more than 70 countries throughout the world. CTEK is also a reliable OEM supplier to many of the world's most prestigious car and motorcycle manufacturers.

\*) Back current drain is the current that drains the battery if the charger is not connected to the mains. CTEK chargers have a very low back current.

\*\*) The quality of the charging voltage and charging current is very important. A high current ripple heats up the battery which has an aging effect on the positive electrode. High voltage ripple could harm other equipment that is connected to the battery. CTEK battery chargers produce very clean voltage and current

equipment that is connected to the battery. CTEK battery chargers produce very clean voltage and current with low ripple.

# For more information visit WWW.CTEK.COM

All products and product specifications are subject to change without notice, to improve reliability, function or design. In the event of product error, we reserve the right to inspect the product and verify the fault. All product returns are subject to our standard warranty terms.

