AUTO CHARGER FOR **/EHICLES** UNCTION

The CT5 START/STOP battery charger and maintainer has been specially designed to charge and maintain batteries in Start/Stop vehicles.

FAST START/STOP CHARGING

Start/Stop technology is great for the environment but it can put a considerable strain on your battery, especially if it's in an older car. By keeping the battery fully charged, you can take full advantage of all the Start/Stop technology benefits, such as better fuel efficiency and lower CO2 emissions. If you only make short journeys, use the CT5 START/STOP once a month to keep your battery in peak condition. And if you're going away on holiday, just connect the charger to the battery to make sure your car's ready to go when you return.

PRACTICAL AND SIMPLE TO USE

The CT5 START/STOP charger is a practical and simple to use charger with an easy to understand display, It is non-sparking, reverse polarity protected and shortcircuit proof, and comes with a 5 year warranty.

- Fully optimized for cars with Start/Stop technology, e.g. AGM and EFB batteries
- No buttons to press fully automatic charging
- Simple to use with an easy to understand display
- Reverse polarity protected
- Non sparking

mmo

CHECK CHARGE CARE

manner

5-year warranty





DACID BATTERIE

h



TECHNICAL DATA

INPUT	220-240 VAC, 50-60 Hz, 0.5 A
OUTPUT	14.55 V, 3.8 A
CHARGER TYPE	Multistage fully automatic charger
BATTERY TYPES	12 V: WET, MF, Ca/Ca, AGM, EFB, GEL
BATTERY CAPACITY	14–130 Ah
START VOLTAGE	2.0 V
BACK CURRENT DRAIN*	Corresponding to less than 1.5 Ah/month
AMBIENT OPERATING TEMPERATURE	-20 °C to +50 °C
TEMPERATURE COMPENSATION	Built in charge voltage compensation according to ambient temperature
BATTERY CHEMISTRY	Lead acid
DEGREE OF PROTECTION	IP65
WARRANTY	5 years

GUARANTEED QUALITY WITH CTEK

CTEK customer support is available to answer any questions related to charging and CTEK chargers. Safety, simplicity and flexibility characterizes all products and solutions developed and sold by CTEK. CTEK supply chargers to more than 70 countries throughout the world. CTEK is also a reliable OEM supplier to many of the world's most prestigious car and motorcycle manufacturers.

For more information visit WWW.CTEK.COM

*) Back current drain is the current that drains the battery if the charger is not connected to the mains. CTEK chargers have a very low back current.

